



. . . c o n n e c t i n g   y o u r   b u s i n e s s

## LANCOM OAP-382

Dual-radio 802.11n outdoor access point with fiber-optic connector for maximum performance

- Two integrated 300 Mbps wireless modules for simultaneous operations with IEEE 802.11a/b/g/n
- Versatility from fiber-optic connector and Gigabit Ethernet
- Power over Ethernet for easy installation away from power supplies
- Optional external 48V power supply
- Professional management functions, IEEE 802.11i/WPA2, Multi-SSID and VLAN
- Robust IP-66 protective housing
- Integrated heating and cooling ensures reliability even at extreme temperatures (-25°C to +50°C)

The LANCOM OAP-382 outdoor access point is the right choice for anybody taking high-speed 802.11n wireless LAN to outdoor areas. Its two radio modules make this access point suitable for a wide range of applications: For example, it can operate as a relay station in a link to a backbone while simultaneously providing Internet access for WLAN clients. With its water-jet resistant IP-66 housing, integrated heating and cooling, and the sturdy fittings for wall and pole-mounting, the device can be operated wherever the highest standards for stability and robustness apply—be it in the mountains or from rooftop to rooftop in the city. The LANCOM OAP-382 can be easily and economically mounted up to 50 m from the nearest power supply thanks to Power over Ethernet. In case you have longer distances, you are recommended to use the LANCOM fiber kit and the LANCOM OAP-380 PSU.

#### **More flexibility.**

The LANCOM OAP-382 can be networked via Ethernet or fiber optics. The externally accessible SFP slot provides a variety of options for implementing the fiber-optic connection. The device also offers versatility in the choice of power supply: Depending on the local situation, the LANCOM 382-OAP can be powered either by the supplied Gigabit High Power PoE injector or via an optionally available 48V cable.

#### **More security.**

LANCOM ensures the highest security standards as it supports a comprehensive range of encryption and authentication mechanisms, including 802.11i, 802.1x, and WPA2. With the aid of Multi-SSID and protocol filters, up to 8 different user groups can each be assigned with different levels of security. VLAN technology, matured quality-of-service functions and bandwidth limitation enable the reliable transmission of video and multimedia data.

#### **More management.**

A management system is vital outdoors where conditions are difficult, for example when it is hard to see the LEDs on an access point mounted on a tall mast. The free LCMS LANCOM Management System allows the monitoring of all device functions and provides an overview of the entire network. For example, it is possible to check whether the access points are transmitting and, if so, on which channels, how much data each one is sending, which clients are logged in and where, what encryption method is active, and a whole lot more. The LANCOM Management System also helps you to optimize performance over wireless bridges. Additionally, the LANCOM OAP-382 supports TACACS+. Using the AAA protocol ("authentication, authorization, accounting") it is possible to track all activities relating to the configuration of the access point.

#### **More reliability for the future.**

LANCOM products are fundamentally designed for a product life spanning several years. They are equipped with hardware dimensioned for the future. Even reaching back to older product generations, updates to the LANCOM Operating System—LCOS—are available several times a year, free of charge and offering major features.

WLAN	
Frequency band 2.4 GHz and 5 GHz	2400 -2483.5 MHz (ISM) and 5150-5825 MHz (depending on country-specific restrictions)
Data rates IEEE 802.11b/g	54 Mbps to IEEE 802.11g (fallback to 48, 36, 24, 18, 12, 9, 6 Mbps, Automatic Rate Selection) compatible to IEEE 802.11b (11, 5.5, 2, 1 Mbps, Automatic Rate Selection), IEEE 802.11 b/g compatibility mode or pure g or pure b
Data rates IEEE 802.11a/ h	54 Mbps (fallback to 48, 36, 24, 18, 12, 9, 6 Mbps, Automatic Rate Selection), fully compatible with TPC (adjustable power output) and DFS (automatic channel selection, radar detection) according to EN 301 893 and EN 302 502
Range (outdoor / P2P)	More than 20 km in 5 GHz. See our LANCOM Antenna Distance Calculator under <a href="http://www.lancom.de">www.lancom.de</a>
Output power at radio module, 2.4 GHz	IEEE 802.11b: +19 dBm @ 1 and 2 Mbps, +19 dBm @ 5.5 und 11 Mbps IEEE 802.11g: +18 dBm @ 6 to 36 Mbps, +17 dBm @ 48 Mbps, +16 dBm @ 54 Mbps IEEE 802.11n: +19 dBm @ 6,5/13 Mbps (MCS0/8, 20 MHz), +10 dBm @ 65/130 Mbps (MCS7/15, 20 MHz), +17 dBm @ 15/30 Mbps (MCS0/8, 40 MHz), +10 dBm @ 150/300 Mbps (MCS7/15, 40 MHz)
Output power at radio module, 5 GHz	IEEE 802.11a/h: +18 dBm @ 6 to 24 Mbps, +17 dBm @ 36 Mbps, +16 dBm @ 48 Mbps, +15 dBm @ 54 Mbps IEEE 802.11n: +18 dBm @ 6,5/13 Mbps (MCS0/8, 20 MHz), +10 dBm @ 65/130 Mbps (MCS7/15, 20 MHz), +17 dBm @ 15/30 Mbps (MCS0/8, 40 MHz), +10 dBm @ 150/300 Mbps (MCS7/15, 40 MHz)
Output power at radio module, 2.4 GHz (WLAN-2)	IEEE 802.11b: 19 dBm @ 5.5 and 11 Mbps IEEE 802.11g: 16 dBm @ 54 Mbps IEEE 802.11n: 15 dBm @ 65/130 Mbps (MCS7, 20 MHz) 14 dBm @ 150/300 Mbps (MCS7, 40 MHz)
Output power at radio module, 5 GHz (WLAN-2)	IEEE 802.11a/h: +14 dBm @ 54 Mbps IEEE 802.11n: +12 dBm @ 65/130 Mbps (MCS7, 20 MHz) +11 dBm @ 150/300 Mbps (MCS7, 40 MHz)
Max. radiated power (EIRP), 2.4 GHz band	IEEE 802.11b/g: Up to 20 dBm / 100 mW EIRP (transmission power control according to TPC)
Max. radiated power (EIRP), 5 GHz band	IEEE 802.11a/h: Up to 30 dBm / 1000 mW or up to 36 dBm / 4000 mW EIRP (depending on national regulations on channel usage and subject to further obligations such as TPC and DFS)
Minimum transmission power	Transmission power reduction in software in 1 dB steps to min. 0.5 dBm
Receiver sensitivity 2.4 GHz	IEEE 802.11b: -91 dBm @ 11 Mbps, -96 dBm @ 1 Mbps; IEEE 802.11g: -96 dBm @ 6 Mbps, -83 dBm @ 54 Mbps; IEEE 802.11n: -96 dBm @ 6,5 Mbps (MCS0, 20 MHz), -79 dBm @ 65 Mbps (MCS7, 20 MHz); -93 dBm @ 13 Mbps (MCS8, 20 MHz), -77 dBm @ 130 Mbps (MCS15, 20 MHz); -90 dBm @ 15 Mbps (MCS0, 40 MHz), -75 dBm @ 150 Mbps (MCS7, 40 MHz); -90 dBm @ 30 Mbps (MCS8, 40 MHz), -73 dBm @ 300 Mbps (MCS15, 40 MHz)
Receiver sensitivity 5 GHz	IEEE 802.11a/h: -95 dBm @ 6 Mbps, -82 dBm @ 54 Mbps; IEEE 802.11n: -95 dBm @ 6,5 Mbps (MCS0, 20 MHz), -77 dBm @ 65 Mbps (MCS7, 20 MHz); -94 dBm @ 13 Mbps (MCS8, 20 MHz), -74 dBm @ 130 Mbps (MCS15, 20 MHz); -91 dBm @ 15 Mbps (MCS0, 40 MHz), -75 dBm @ 150 Mbps (MCS7, 40 MHz); -90 dBm @ 30 Mbps (MCS8, 40 MHz), -71 dBm @ 300 Mbps (MCS15, 40 MHz)
Receiver sensitivity 2.4 GHz (WLAN-2)	IEEE 802.11b: -90 dBm @ 11 Mbps IEEE 802.11g: -73 dBm @ 54 Mbps IEEE 802.11n: -69 dBm @ 65 Mbps (MCS7, 20 MHz) -65 dBm @ 150 Mbps (MCS7, 40 MHz)
Receiver sensitivity 5 GHz (WLAN-2)	IEEE 802.11a/h: -72 dBm @ 54 Mbps IEEE 802.11n: -69 dBm @ 65 Mbps (MCS7, 20 MHz) -67 dBm @ 150 Mbps (MCS7, 40 MHz)
Radio channels 2.4 GHz	Up to 13 channels, max. 3 non-overlapping (depending on country-specific restrictions)
Radio channels 5 GHz	Up to 26 non-overlapping channels (available channels and further obligations such as automatic DFS dynamic channel selection depending on national regulations)
Roaming	Seamless handover between radio cells, IAPP support with optional restriction to an ARF context, IEEE 802.11d support
Opportunistic Key Caching**	Opportunistic key caching allows fast roaming processes between access points. WLAN installations utilizing a WLAN controller and IEEE 802.1X authentication cache the access keys of the clients and are transmitted by the WLAN controller to all managed access points
Fast roaming*	Based on IEEE 802.11r, allows fast roaming procedures between access points. This is possible by using IEEE 802.1X authentication or pre-shared keys in controller based WLAN installations, which save the access keys temporarily and distribute them to the managed access points.
Concurrent WLAN clients	Up to 30 clients per radio (recommended), 512 clients (max.)
Fast client roaming	With background scanning, moving LANCOM 'client mode' access points pre-authenticate to alternative access points which offer a better signal before Roaming fails
VLAN	VLAN ID definable per interface, WLAN SSID, point-to-point connection and routing context (4094 IDs) IEEE 802.1q
Dynamic VLAN assignment	Dynamic VLAN assignment for target user groups based on MAC addresses, BSSID or SSID by means of external RADIUS server.
Q-in-Q tagging	Support of layered IEEE 802.1q VLANs (double tagging)
Multi-SSID	Simultaneous use of up to 8 independent WLAN networks per WLAN interface
IGMP snooping	Support for Internet Group Management Protocol (IGMP) in the WLAN bridge for WLAN SSIDs and LAN interfaces for specific switching of multicast packets (devices with integrated WLAN only). Automated detection of multicast groups. Configurable action for multicast packets without registration. Configuration of static multicast group members per VLAN ID. Configuration of query simulation for multicast membership per VLAN ID
Protected Management Frames	Protection of WLAN Management Frames, based on the standard IEEE 802.11w, against man-in-the-middle attacks by using Message Integrity Codes (MIC)

WLAN	
Security	IEEE 802.11i / WPA2 with passphrase (WPA2-Personal) or IEEE 802.1X (WPA2-Enterprise) and hardware-accelerated AES, closed network, WEP64, WEP128, WEP152, user authentication, IEEE 802.1x /EAP, LEPS, WPA1/TKIP
EAP Types	EAP-TLS, EAP-TTLS/MSCAPv2, PEAPv0/EAP-MSCHAPv2, PEAPv1/EAP-GTC, EAP-SIM, EAP-AKA, EAP-AKA Prime, EAP-FAST
RADIUS server	Integrated RADIUS server for MAC address list management
EAP server	Integrated EAP server for authentication of IEEE 802.1X clients via EAP-TLS, EAP-TTLS, PEAP, MSCHAP or MSCHAPv2
RADIUS Accounting per SSID	A RADIUS server can be set for each individual SSID
Quality of Service	Prioritization according to Wireless Multimedia Extensions (WME, subset of IEEE 802.11e)
U-APSD/WMM Power Save	Extension of power saving according to IEEE 802.11e by Unscheduled Automatic Power Save Delivery (equivalent to WMM Power Save). U-APSD supports the automatic switch of clients to a doze mode. Increased battery lifetime for telephone calls over VoWLAN (Voice over WLAN)
bandwidth limitation per WLAN client	Maximum transmit and receive bandwidth and an individual VLAN ID can be assigned to each WLAN client (MAC address)
bandwidth limitation per SSID	Maximum transmit and receive bandwidth can be assigned to each SSID
Broken link detection	If the link of a chosen LAN interface breaks down, a WLAN module can be deactivated to let the associated clients search for a new base station
Background scanning	Detection of rogue AP's and the channel information for all WLAN channels during normal AP operation. The Background Scan Time Interval defines the time slots in which an AP or Router searches for a foreign WLAN network in its vicinity. The time interval can be specified in either milliseconds, seconds, minutes, hours or days
Client detection	Rogue WLAN client detection based on probe requests
IEEE 802.1X supplicant	Authentication of an access point in WLAN client mode at another access point via IEEE 802.1X (EAP-TLS, EAP-TTLS and PEAP)
Layer-3 Tunneling	Layer-3 Tunneling in conformity with the CAPWAP standard allows the bridging of WLANs per SSID to a separate IP subnet. Layer-2 packets are encapsulated in Layer-3 tunnels and transported to a LANCOM WLAN controller. By doing this the access point is independent of the present infrastructure of the network. Possible applications are roaming without changing the IP address and compounding SSIDs without using VLANs.
IEEE 802.11u	The WLAN standard IEEE 802.11u (Hotspot 2.0) allows for a seamless transition from the cellular network into WLAN hotspots. Authentication methods using SIM card information, certificates or username and password, enable an automatic, encrypted login to WLAN hotspots - without the need to manually enter login credentials.
PRP	Packet loss of point-to-point connections can be reduced by using the Parallel Redundancy Protocol with dual radio access points due to parallel data transmissions
Auto WDS**	Auto WDS allows wireless integration of access points in existing WLAN infrastructure, including management via WLAN controller.
*) Note	The effective distances and transmission rates that can be achieved are depending of the site RF conditions
***) Note	Only in installations with WLAN controller
LANCOM Active Radio Control	
Client Steering*	WLAN clients are directed actively to the best available access point to provide the best overall load balancing and the highest possible bandwidth for each client. Client Steering can be based on client number, frequency band, and signal strength.
Band Steering	Steering of WLAN clients towards the 5 GHz frequency band by restricting the access to the 2.4 GHz band.
RF Optimization*	Automatic selection of optimal WLAN channels. Due to reduced channel overlaps, WLAN clients benefit from an improved data throughput. In controller-based installations, an automatic selection of optimal channels is conducted for all managed access points.
Adaptive Noise Immunity	By using adaptive noise immunity an access point can cut out sources of interferences in the radio field and focusses on clients with a sufficient signal strength. Therefore, WLAN clients profit by having a higher data throughput available due to less interferences
*) Note	Only in installations with WLAN controller
IEEE 802.11n Features	
MIMO	MIMO technology is a technique which uses multiple transmitters to deliver multiple data streams via different spatial channels. Depending on the existing RF conditions the throughput is multiplied with MIMO technology.
40 MHz Channels	Two adjacent 20 MHz channels are combined to create a single 40 MHz channel. Depending on the existing RF Conditions channel bonding doubles the throughput.
20/40MHz Coexistence Mechanisms in the 2.4GHz Band	Support of coexisting accesspoints with 20 and 40MHz channels in 2.4GHz band.
MAC Aggregation and Block Acknowledgement	MAC Aggregation increase the IEEE 802.11 MAC efficiency by combining MAC data frames and sending it out with a single header. The receiver acknowledges the combined MAC frame with a Block Acknowledgement. Depending on existing RF conditions, this technique improves throughput by up to 20%.

IEEE 802.11n Features	
Maximal Ratio Combining (MRC)	Maximal Ratio Combining (MRC) enables the receiver (access point), in combination with multiple antennas, to optimally combine MIMO signals to improve the client reception at long-range.
Short Guard Interval	The guard interval is the time between OFDM symbols in the air. IEEE 802.11n gives the option for a shorter 400 nsec guard interval compared to the legacy 800 nsec guard interval. Under ideal RF conditions this increases the throughput by upto 10%
BFWA*	Support for Broadband Fixed Wireless Access in 5.8 GHz band with up to 4 Watts EIRP for WLAN point-to-point links according to the national regulations of your country, special antennas required
*) Note	The use of BFWA is subject to country specific regulation
WLAN operating modes	
WLAN access point	Infrastructure mode (autonomous operation or managed by LANCOM WLAN controller)
WLAN bridge	Point-to-multipoint connection of up to 16 Ethernet LANs (mixed operation optional), broken link detection, blind mode, supports VLAN When configuring Pt-to-Pt links, pre-configured names can be used as an alternative to MAC Addresses for creating a link. Rapid spanning-tree protocol to support redundant routes in Ethernet networks
WLAN router	Use of the LAN connector for simultaneous DSL over LAN, IP router, NAT/Reverse NAT (IP masquerading) DHCP server, DHCP client, DHCP relay server, DNS server, PPPoE client (incl. Multi-PPPoE), PPTP client and server, NetBIOS proxy, DynDNS client, NTP, port mapping, policy-based routing based on routing tags, tagging based on firewall rules, dynamic routing with RIPv2, VRRP
WLAN client	Transparent WLAN client mode for wireless Ethernet extensions, e.g. connecting PCs or printers by Ethernet; up to 64 MAC addresses. Automatic selection of a WLAN profile (max. 8) with individual access parameters depending on signal strength or priority
Firewall	
Stateful inspection firewall	Incoming/Outgoing Traffic inspection based on connection information. Trigger for firewall rules depending on backup status, e.g. simplified rule sets for low-bandwidth backup lines. Limitation of the number of sessions per remote site (ID)
Packet filter	Check based on the header information of an IP packet (IP or MAC source/destination addresses; source/destination ports, DiffServ attribute); remote-site dependant, direction dependant, bandwidth dependant
Extended port forwarding	Network Address Translation (NAT) based on protocol and WAN address, i.e. to make internal webservers accessible from WAN
N:N IP address mapping	N:N IP address mapping for translation of IP addresses or entire networks
Tagging	The firewall marks packets with routing tags, e.g. for policy-based routing; Source routing tags for the creation of independent firewall rules for different ARF contexts
Actions	Forward, drop, reject, block sender address, close destination port, disconnect
Notification	Via e-mail, SYSLOG or SNMP trap
Quality of Service	
Traffic shaping	Dynamic bandwidth management with IP traffic shaping
Bandwidth reservation	Dynamic reservation of minimum and maximum bandwidths, totally or connection based, separate settings for send and receive directions. Setting relative bandwidth limits for QoS in percent
DiffServ/TOS	Priority queuing of packets based on DiffServ/TOS fields
Packet-size control	Automatic packet-size control by fragmentation or Path Maximum Transmission Unit (PMTU) adjustment
Layer 2/Layer 3 tagging	Automatic or fixed translation of layer-2 priority information (IEEE 802.11p-marked Ethernet frames) to layer-3 DiffServ attributes in routing mode. Translation from layer 3 to layer 2 with automatic recognition of IEEE 802.11p-support in the destination device
Security	
Intrusion Prevention	Monitoring and blocking of login attempts and port scans
IP spoofing	Source IP address check on all interfaces: only IP addresses belonging to the defined IP networks are allowed
Access control lists	Filtering of IP or MAC addresses and preset protocols for configuration access
Denial of Service protection	Protection from fragmentation errors and SYN flooding
General	Detailed settings for handling reassembly, PING, stealth mode and AUTH port
URL blocker	Filtering of unwanted URLs based on DNS hitlists and wildcard filters
Password protection	Password-protected configuration access can be set for each interface
Alerts	Alerts via e-mail, SNMP-Traps and SYSLOG
Authentication mechanisms	EAP-TLS, EAP-TTLS, PEAP, MS-CHAP, MS-CHAPv2 as EAP authentication mechanisms, PAP, CHAP, MS-CHAP and MS-CHAPv2 as PPP authentication mechanisms

Security	
WLAN protocol filters	Limitation of the allowed transfer protocols, source and target addresses on the WLAN interface
IP redirect	Fixed redirection of any packet received over the WLAN interface to a dedicated target address
High availability / redundancy	
VRRP	VRRP (Virtual Router Redundancy Protocol) for backup in case of failure of a device or remote station. Enables passive standby groups or reciprocal backup between multiple active devices including load balancing and user definable backup priorities
FirmSafe	For completely safe software upgrades thanks to two stored firmware versions, incl. test mode for firmware updates
Line monitoring	Line monitoring with LCP echo monitoring, dead-peer detection and up to 4 addresses for end-to-end monitoring with ICMP polling
Routing functions	
Router	IP and NetBIOS/IP multi-protocol router
Advanced Routing and Forwarding	Separate processing of 16 contexts due to virtualization of the routers. Mapping to VLANs and complete independent management and configuration of IP networks in the device, i.e. individual settings for DHCP, DNS, Firewalling, QoS, VLAN, Routing etc. Automatic learning of routing tags for ARF contexts from the routing table
HTTP	HTTP and HTTPS server for configuration by web interface
DNS	DNS client, DNS server, DNS relay, DNS proxy and dynamic DNS client
DHCP	DHCP client, DHCP relay and DHCP server with autodetection. Cluster of several LANCOM DHCP servers per context (ARF network) enables caching of all DNS assignments at each router. DHCP forwarding to multiple (redundant) DHCP servers
NetBIOS	NetBIOS/IP proxy
NTP	NTP client and SNTP server, automatic adjustment for daylight-saving time
Policy-based routing	Policy-based routing based on routing tags. Based on firewall rules, certain data types are marked for specific routing, e.g. to particular remote sites or lines
Dynamic routing	Dynamic routing with RIPv2. Learning and propagating routes; separate settings for LAN and WAN. Extended RIPv2 including HopCount, Output Delay, Poisoned Reverse, Triggered Update for LAN (acc. to RFC 2453) and WAN (acc. to RFC 2091) as well as filter options for propagation of routes. Definition of RIP sources with wildcards
DHCPv6	DHCPv6 client, DHCPv6 server, DHCPv6 relay, stateless- and stateful mode, IPv6 address (IA_NA), prefix delegation (IA_PD), DHCPv6 reconfigure (server and client)
Layer 2 functions	
ARP lookup	Packets sent in response to LCOS service requests (e.g. for Telnet, SSH, SNTP, SMTP, HTTP(S), SNMP, etc.) via Ethernet can be routed directly to the requesting station (default) or to a target determined by ARP lookup
LLDP	Automatic discovery of network topology in layer 2 networks (Link Layer Discover Protocol)
DHCP option 82	DHCP relay agent information (option 82) can be insterted on devices with WLAN bridge (RFC 3046)
IPv6 layer 2 protocol filter	Router advertisement snooping blocks illegal IPv6 router advertisements in the WLAN bridge. DHCPv6 snooping blocks all illegal DHCPv6 servers. The lightweight DHCPv6 relay agent (LDRA) can insert relay agent information on layer 2.
LAN protocols	
IP	ARP, proxy ARP, BOOTP, DHCP, DNS, HTTP, HTTPS, IP, ICMP, NTP/SNTP, NetBIOS, PPPoE (server), RADIUS, RIP-1, RIP-2, RTP, SIP, SNMP, TCP, TFTP, UDP, VRRP, VLAN
Rapid Spanning Tree	IEEE 802.1d Spanning Tree and IEEE 802.1w Rapid Spanning Tree support for dynamic path selection with redundant layer 2 connections
IPv6	NDP, stateless address autoconfiguration (SLAAC), stateful address autoconfiguration (with DHCPv6), router advertisements, ICMPv6, DHCPv6, DNS, HTTP, HTTPS, PPPoE, RADIUS, TCP, UDP, SMTP
IPv6	
Dual Stack	IPv4/IPv6 dual stack
IPv6 compatible LCOS applications	WEBconfig, HTTP, HTTPS, SSH, Telnet, DNS, TFTP, Firewall, RAS dial-in
WAN protocols	
Ethernet	PPPoE, Multi-PPPoE, ML-PPP, PPTP (PAC or PNS), L2TPv2 (LAC or LNS) and IPoE (with or without DHCP), RIP-1, RIP-2, VLAN, IP
IPv6	IPv6 over PPP (IPv6 and IPv4/IPv6 dual stack session), IPoE (autoconfiguration, DHCPv6 or static)
Tunneling protocols (IPv4/IPv6)	6to4, 6in4, 6rd (static and via DHCP), Dual Stack Lite (IPv4 in IPv6 tunnel)

WAN operating mode	
xDSL (ext. modem)	ADSL1, ADSL2 or ADSL2+ with external ADSL2+ modem
Interfaces	
Ethernet port	1 Gigabit Ethernet Port, 10/100/1000 MBit/s, High Power PoE (56V) with supplied PoE Injector only
SFP Slot	Harting SFP Slot (HAN 3A SFP) for pluggable SFP module, copper SFP modules are not supported, SFP module and fiber cable not included in delivery
External antenna connectors	Four N connectors for external LANCOM AirLancer Extender antennas or for antennas from other vendors. Please respect the restrictions which apply in your country when setting up an antenna system. For information about calculating the correct antenna setup, please refer to <a href="http://www.lancom-systems.eu">www.lancom-systems.eu</a>
LCMS (LANCOM Management System)	
LANconfig	Configuration program for Microsoft Windows, incl. convenient Setup Wizards. Optional group configuration, simultaneous remote configuration and management of multiple devices over IP connection (HTTPS, HTTP, SSH, TFTP). A tree view of the setting pages like in WEBconfig provides quick access to all settings in the configuration window. Password fields which optionally display the password in plain text and can generate complex passwords. Configuration program properties per project or user. Automatic storage of the current configuration before firmware updates. Exchange of configuration files between similar devices, e.g. for migrating existing configurations to new LANCOM products. Detection and display of the LANCOM managed switches. Extensive application help for LANconfig and parameter help for device configuration. LANCOM QuickFinder as search filter within LANconfig and device configurations that reduces the view to devices with matching properties. Central configuration of each management port.
LANmonitor	Monitoring application for Microsoft Windows for (remote) surveillance and logging of the status of LANCOM devices and connections, incl. PING diagnosis and TRACE with filters and save to file. Search function within TRACE tasks. Wizards for standard diagnostics. Export of diagnostic files for support purposes (including bootlog, sysinfo and device configuration without passwords). Graphic display of key values (marked with an icon in LANmonitor view) over time as well as table for minimum, maximum and average in a separate window, e. g. for Rx, Tx, CPU load, free memory. Monitoring of the LANCOM managed switches. Flick easily through different search results by LANCOM QuickFinder
WLANmonitor	Monitoring application for Microsoft Windows for the visualization and monitoring of LANCOM WLAN installations, incl. Rogue AP and Rogue Client visualization. LANCOM QuickFinder as search filter that reduces the view to devices with matching properties
Firewall GUI	Graphical user interface for configuring the object-oriented firewall in LANconfig: Tabular presentation with symbols for rapid understanding of objects, choice of symbols for objects, objects for actions/Quality of Service/remote sites/services, default objects for common scenarios, individual object definition (e.g. for user groups)
Automatic software update	Voluntary automatic updates for LCMS. Search online for LCOS updates for devices managed by LANconfig on the myLANCOM download server (myLANCOM account mandatory). Updates can be applied directly after the download or at a later time
Management	
WEBconfig	Integrated web server for the configuration of LANCOM devices via Internet browsers with HTTPS or HTTP. Similar to LANconfig with a system overview, SYSLOG and events display, symbols in the menu tree, quick access with side tabs. WEBconfig also features Wizards for basic configuration, security, Internet access, LAN-LAN coupling. Online help for parameters in LCOS menu tree
LANCOM Layer 2 Management (emergency management)	The LANCOM Layer 2 Management protocol (LL2M) enables an encrypted access between the command line interfaces of two LANCOM device directly via a Layer 2 connection
Alternative boot configuration	During rollout devices can be preset with project- or customer-specific settings. Up to two boot- and reset-persistent memory spaces can store customized configurations for customer-specific standard settings (memory space '1') or as a rollout configuration (memory space '2'). A further option is the storage of a persistent standard certificate for the authentication of connections during rollouts
Device SYSLOG	SYSLOG buffer in the RAM (size depending on device memory) to store events for diagnosis. Default set of rules for the event protocol in SYSLOG. The rules can be modified by the administrator. Display and saving of internal SYSLOG buffer (events) from LANCOM devices with LANmonitor, display only with WEBconfig
Access rights	Individual access and function rights for up to 16 administrators. Alternative access control on a per parameter basis with TACACS+
User administration	RADIUS user administration for dial-in access (PPP/PPTP). Support for RADSEC (Secure RADIUS) providing secure communication with RADIUS servers
Remote maintenance	Remote configuration with Telnet/SSL, SSH (with password or public key), browser (HTTP/HTTPS), TFTP or SNMP, firmware upload via HTTP/HTTPS or TFTP
TACACS+	Support of TACACS+ protocol for authentication, authorization and accounting (AAA) with reliable connections and encrypted payload. Authentication and authorization are separated completely. LANCOM access rights are converted to TACACS+ levels. With TACACS+ access can be granted per parameter, path, command or functionality for LANconfig, WEBconfig or Telnet/SSH. Each access and all changes of configuration are logged. Access verification and logging of SNMP Get and Set requests. WEBconfig supports the access rights of TACACS+ and choice of TACACS+ server at login. LANconfig provides a device login with the TACACS+ request conveyed by the addressed device. Authorization to execute scripts and each command within them by checking the TACACS+ server's database. CRON, action-table and script processing can be diverted to avoid TACACS+ to relieve TACACS+ servers. Redundancy by setting several alternative TACACS+ servers. Configurable option to fall back to local user accounts in case of connection drops to the TACACS+ servers. Compatibility mode to support several free TACACS+ implementations
RADIUS	Support of RADIUS protocol for authentication of configuration access. Administrative privileges can be assigned for each administrator.

Management	
Remote maintenance of 3rd party devices	A remote configuration for devices behind der LANCOM can be accomplished (after authentication) via tunneling of arbitrary TCP-based protocols, e.g. for HTTP(S) remote maintenance of VoIP phones or printers of the LAN. Additionally, SSH and Telnet client allow to access other devices from a LANCOM device with an interface to the target subnet if the LANCOM device can be reached at its command line interface
TFTP & HTTP(S) client	For downloading firmware and configuration files from a TFTP, HTTP or HTTPS server with variable file names (wildcards for name, MAC/IP address, serial number), e.g. for roll-out management. Commands for live Telnet session, scripts or CRON jobs. HTTPS Client authentication possible by username and password or by certificate
SSH & Telnet client	SSH-client function compatible to Open SSH under Linux and Unix operating systems for accessing third-party components from a LANCOM router. Also usable when working with SSH to login to the LANCOM device. Support for certificate- and password-based authentication. Generates its own key with sshkeygen. SSH client functions are restricted to administrators with appropriate rights. Telnet client function to login/administer third party devices or other LANCOM devices from command line interface
HTTPS Server	Option to choose if an uploaded certificate or the default certificate is used by the HTTPS server
Large Scale Monitor (LSM)	The LANCOM Large Scale Monitor (LSM) is a professional tool for monitoring medium-sized to large-scale networks with 25 to 1,000 network components. Designed especially for LANCOM components including WLAN access points, controllers, switches, and routers, this system based on open-source components additionally allows for the monitoring of third-party products such as servers and printers. Problems in the network are clearly displayed in tables or graphical floor plans, and they trigger alert messages via e-mail if certain threshold values are not maintained.
Security	Access rights (read/write) over WAN or (W)LAN can be set up separately (Telnet/SSL, SSH, SNMP, HTTPS/HTTP), access control list
Scripting	Scripting function for batch-programming of all command-line parameters and for transferring (partial) configurations, irrespective of software versions and device types, incl. test mode for parameter changes. Utilization of timed control (CRON) or connection establishment and termination to run scripts for automation. Scripts can send e-mails with various command line outputs as attachments
Load commands	LoadFirmware, LoadConfig and LoadScript can be executed conditionally in case certain requirements are met. For example, the command LoadFirmware could be executed on a daily basis and check each time if the current firmware is up to date or if a new version is available. In addition, LoadFile allows the upload of files including certificates and secured PKCS#12 containers
SNMP	SNMP management via SNMPv2, private MIB exportable by WEBconfig, MIB II
Timed control	Scheduled control of parameters and actions with CRON service
Diagnosis	Extensive LOG and TRACE options, PING and TRACEROUTE for checking connections, LANmonitor status display, internal logging buffer for SYSLOG and firewall events, monitor mode for Ethernet ports
LANCOM WLAN controller	Supported by all LANCOM WLAN controller (separate optional hardware equipment for installation, optimization, operating and monitoring of WLAN networks, except for P2P connections)
Statistics	
Statistics	Extensive Ethernet, IP and DNS statistics; SYSLOG error counter
Accounting	Connection time, online time, transfer volumes per station. Snapshot function for regular read-out of values at the end of a billing period. Timed (CRON) command to reset all counters at once
Export	Accounting information exportable via LANmonitor and SYSLOG
Hardware	
Power supply	Via Power over Ethernet (max. distance between access point, injector and switch 50 m), 1 x PoE Injector supplied*
Power supply	1 x 48 V DC with optional 48V cable (not included in delivery)
Environment	-25° C to +50° C at 95% max. humidity (non condensing)
Housing	235 mm x 210 mm x 80 mm (W x H x D), 3.4 kg, robust metal housing, IP 66 protection rating, ready for wall and pole mounting, 6 LEDs for status display
Power consumption (max)	37 Watts when heating is active, 27 Watts when heating is not active
*) Note	PoE operates with the supplied PoE adapter only
Declarations of conformity*	
CE	EN 60950-1, EN 301 489-1, EN 301 489-17
2.4 GHz WLAN	EN 300 328
5 GHz WLAN	EN 301 893, EN 302 502
Notifications	Certifications notified in Germany, Belgium, Netherlands, Luxembourg, Austria, Switzerland, UK, Italy, Spain, France, Portugal, Czech Republic, Denmark
IPv6	IPv6 Ready Gold
*) Note	You will find all declarations of conformity in the products section of our website at <a href="http://www.lancom-systems.eu">www.lancom-systems.eu</a>

Scope of delivery	
Manual	Hardware Quick Reference (EN, DE), Installation Guide (DE/EN/FR/ES/IT/PT/NL)
CD/DVD	Data medium with management software (LANconfig, LANmonitor, WLANmonitor, LANCAPI) and documentation
Cable	Water-resistant, UV-resistant Ethernet PoE cable with water-resistant screw connector, 15m
Cable	AirLancer Adapter NP-NP 25 cm, connector for external LANCOM outdoor antennas
Antenna	Four 3 dBi dipole dual-band antennas
Power supply unit	Via Power over Ethernet*, 1 x Gigabit High Power PoE (50W/56V) Injector supplied
*) Note	Power over Ethernet operates with the supplied PoE adapter only
Support	
Warranty	3 years support via hotline and Internet KnowledgeBase
Software updates	Regular free updates (LCOS operating system and LANCOM Management System) via Internet
Options	
Advance Replacement	LANCOM Next Business Day Service Extension IAP & OAP, item no. 61412
Warranty Extension	LANCOM 2-Year Warranty Extension IAP & OAP, item no. 61415
Public Spot	LANCOM Public Spot Option (authentication and accounting software for hotspots, incl. Voucher printing through Standard PC printer), item no. 60642
Accessories	
LANCOM WLC-4006+ (EU/UK/US)	LANCOM WLAN controller for central management of 6 (opt. up to 30) LANCOM access points and WLAN routers, item no. 62035 (EU), item no. 62036 (UK) and item no. 62037 (US)
LANCOM WLC-4025+ (EU/UK/US)	LANCOM WLAN controller for central management of 25 (opt. up to 100) LANCOM access points and WLAN routers, item no. 61378, item no. Art.-Nr. 61379 and item no. 61384 (US)
LANCOM WLC-4025 (EU/UK)	LANCOM WLAN controller for central management of 25 (opt. up to 100) LANCOM access points and WLAN routers, item no. 61550 (EU) and item no. 61551 (UK) - only stock devices, article is no longer available
LANCOM WLC-4100 (EU/UK)	LANCOM WLAN controller for central management of 100 (opt. up to 1000) LANCOM access points and WLAN routers, item no. 61369 (EU) and item no. 61377 (UK)
External antenna	AirLancer Extender O-30 2.4 GHz outdoor antenna, item no. 60478
External antenna	AirLancer Extender O-70 2.4 GHz outdoor antenna, item no. 60469
External antenna	AirLancer Extender O-9a 5 GHz outdoor antenna, item no. 61220
External antenna	AirLancer Extender O-18a 5 GHz outdoor antenna, item no. 61210
External antenna*	AirLancer Extender O-D80g 2.4 GHz 'dual linear' polarisation diversity outdoor sector antenna, item no. 61221
External antenna*	AirLancer Extender O-D60a 5 GHz 'dual linear' polarisation diversity outdoor sector antenna, item no. 61222
External antenna	AirLancer Extender O-360ag dual-band omnidirectional outdoor antenna, item no. 61223
External antenna*	AirLancer Extender O-D9a 5 GHz 'dual linear' polarisation diversity outdoor antenna, item no. 61224
1000Base-SX SFP module	LANCOM SFP-SX-LC2, item no. 61558
Antenna cable	AirLancer cable NJ-NP 3m antenna cable extension for connection with LANCOM outdoor antennas, item no. 61230
Antenna cable	AirLancer cable NJ-NP 6m antenna cable extension for connection with LANCOM outdoor antennas, item no. 61231
Antenna cable	AirLancer cable NJ-NP 9m antenna cable extension for connection with LANCOM outdoor antennas, item no. 61232
Surge arrestor (antenna cable)	AirLancer Extender SA-5L surge arrestor (2.4 and 5 GHz), to be integrated between Access Point and antenna, item no. 61553
Surge arrestor (LAN cable)	AirLancer Extender SA-LAN surge arrestor (LAN cable), item no. 61213
LAN cable (outdoor)	LANCOM OAP-380 Ethernet cable (15 m), item no. 61508
LAN cable (outdoor)	LANCOM OAP-380 Ethernet cable (30 m), item no. 61348
Multimode Fiber-Kit	LANCOM OAP-380 Multimode Fiber-Kit, item no. 61546
Power Cable (Outdoor)	LANCOM OAP-380 Power Cable (15 m), item no. 61545
Power Supply Unit (Outdoor)	LANCOM OAP-380 PSU, 48 V DC Outdoor Power Supply for OAP-382 (230 V AC)

Accessories	
*) Note	The Polarization Diversity antennas require 2 cables and surge arrestors
Item number(s)	
LANCOM OAP-382 (EU)	61542
LANCOM OAP-382 (UK)	61561
LANCOM OAP-382 (bulk 1), excluding cable, antennas and power supply	61544